HF140FF

MINIATURE INTERMEDIATE POWER RELAY



File No.:E134517



File No.:R50149131



File No.:CQC09002030294



Features

- 10A switching capability
- 5kV dielectric strength (between coil and contacts)
- 2.0mm contact gap available
- Sockets available
- Plastic sealed and dust protected types available
- UL insulation system: Class F available
- Environmental friendly product (RoHS compliant)
- Outline Dimensions: (29.0 x 13.0 x 26.3) mm

CONTACT DAT	A
Contact arrangement	2A, 2C
Contact resistance	50mΩ max.(at 1A 24VDC)
Contact material	AgSnO ₂ , AgNi, AgCdO
Contact rating (Res. load)	10A 250VAC 8A 30VDC
Max. switching voltage	250VAC / 30VDC
Max. switching current	10A
Max. switching power	2500VA / 240W
Mechanical endurance	Standard: 1 x 10 ⁷ ops W type(1.5mm): 5 x10 ⁵ ops W type(2.0mm): 3 x10 ⁵ ops
Electrical endurance	1 x 10 ⁵ ops (NO or NC, 10A 250VAC,
	Resistive load, Room temp., 1s on 9s off, 1 x 10 ⁵ ops (NO or NC, 8A 30VDC, Resistive load, Room temp., 1s on 9s off)

CHARACTERISTICS				
Insulation resistance		е	1000MΩ (at 500VDC)	
Between		coil & contacts	5000VAC 1min	
Dielectric	Between contacts sets		3000VAC 1min	
strength			Standard:1000VAC 1min	
	Betweer	open contacts	W type(1.5mm):2000VAC 1min	
			W type(2.0mm):2500VAC 1min	
Surge voltage (between coil & contacts)		een coil & contacts)	10kV (1.2/50 μs)	
Operate time (at nomi. volt.)		mi. volt.)	15ms max.	
Release time (at nomi. volt.)		mi. volt.)	5ms max.	
Humidity			5% to 85% RH	
Ambient temperature		e	-40°C to 85°C	
Shock resistance Functional Destructive		Functional	98m/s ²	
		Destructive	980m/s ²	
Vibration resistance			10Hz to 55Hz 1.5mmDA	
Termination			PCB	
Unit weight			Approx. 18g	
Construction			Plastic sealed, Flux proofed	

COIL	
	Standard: Approx. 530mW
Coil power	W type(1.5mm): Approx. 800mW
	W type(2.0mm): Approx. 1.4W

COIL DATA

at 23°C

Standard type

Nominal Voltage VDC	Pick-up Voltage VDC max.	Drop-out Voltage VDC min.	Max. Voltage VDC *	Coil Resistance Ω
3	2.25	0.3	3.9	17 x (1±10%)
5	3.75	0.5	6.5	47 x (1±10%)
6	4.50	0.6	7.8	68 x (1±10%)
9	6.75	0.9	11.7	160 x (1±10%)
12	9.00	1.2	15.6	275 x (1±10%)
18	13.5	1.8	23.4	620 x (1±10%)
24	18.0	2.4	31.2	1100 x (1±10%)
48	36.0	4.8	62.4	4170 x (1±10%)
60	45.0	6.0	78.0	7000 x (1±10%)

Notes: 1) The data shown above are initial values.

- 2) Please find coil temperature curve in the characteristic curves below.
- 3) UL insulation system: Class F, Class B.



COIL DATA at 23°C

W Type (1.5mm)

Nominal Voltage VDC	Pick-up Voltage VDC max.	Drop-out Voltage VDC min.	Max. Allowable Voltage VDC*	Coil Resistance Ω
3	2.25	0.3	3.3	11.3 x (1±10%)
5	3.75	0.5	5.5	31 x (1±10%)
6	4.50	0.6	6.6	45 x (1±10%)
9	6.75	0.9	9.9	101 x (1±10%)
12	9.00	1.2	13.2	180 x (1±10%)
18	13.5	1.8	19.8	405 x (1±10%)
24	18.0	2.4	26.4	720 x (1±10%)
48	36.0	4.8	52.8	2880 x (1±10%)
60	45.0	6.0	66.0	4500 x (1±10%)

W Type (2.0mm)

Nominal Voltage VDC	Pick-up Voltage VDC max.	Drop-out Voltage VDC min.	Max. Allowable Voltage VDC*	Coil Resistance Ω
5	3.75	0.5	5.5	18 x (1±10%)
6	4.50	0.6	6.6	26 x (1±10%)
9	6.75	0.9	9.9	58 x (1±10%)
12	9.00	1.2	13.2	102 x (1±10%)
24	18.0	2.4	26.4	410 x (1±10%)
48	36.0	4.8	52.8	1650 x (1±10%)

Notes:1) When require pick-up voltage < 75% of nominal voltage,

SAFETY APPROVAL RATINGS


UL/CUL W type		AgCdO		TV-3 125VAC 10A 250VAC 10A 30VDC 1/4HP 240VAC 1/8HP 120VAC
		AgNi		10A 250VAC 10A 30VDC 12A 277VAC/250VAC Resistive at 70°C 1/3HP 125VAC at 40°C
	Standard	AgSnO2	2 Form A	10A 250VAC 10A 30VDC 12A 277VAC/250VAC Resistive at 70°C 1/3HP 125VAC at 40°C 3/4HP 250VAC at 40°C
			2 Form C	10A 250VAC 10A 30VDC 12A 277VAC/250VAC Resistive at 70°C 1/3HP 125VAC at 40°C NO:TV-5 120VAC at 40°C 3/4HP 250VAC at 40°C
		AgCdO	2 Form A	TV-3 125VAC 10A 250VAC
	W type	AgSnO2	2 Form A	12A 277VAC/250VAC Resistive at 70°C 1/3HP 125VAC at 40°C 3/4HP 250VAC at 40°C
TÜV		AgCdO	2 Form A 2 Form C	10A 250VAC 10A 30VDC
		AgNi	2 Form A 2 Form C	12A 250VAC 10A 250VAC
		AgSnO2	2 Form A	12A 250VAC

Notes: 1) All values unspecified are at room temperature.

special order allowed.

2) *The max. allowable voltage in the COIL DATA is coil overdrive voltage, it is the instantaneous max. voltage which the relay coil could endure in a very short time.

²⁾Only typical loads are listed above. Other load specifications can be available upon request.



Notes:1) We recommend flux proofed types for a clean environment (free from contaminations like H2S, SO2, NO2, dust, etc.).


We suggest to choose plastic sealed types and validate it in real application for an unclean environment (with contaminations like H2S, SO2, NO2, dust, etc.).

- 2) Contact is recommended for suitable condition and specifications if water cleaning or surface process is involved in assembling relays on PCB.
- 3) There are two specifications to W type: 1.5mm contact gap and 2.0mm contact gap. The default W type is 1.5mm. So please add the special code "(456)" when releasing order, if 2.0mm contact gap is required.
- 4) The standard type is made of black cover. If smoke cover is required, please add a special suffix (611) when ordering. Please take note that smoke cover is only available for flux proofed type.

OUTLINE DIMENSIONS, WIRING DIAGRAM AND PC BOARD LAYOUT

Unit: mm


Outline Dimensions



Wiring Diagram (Bottom view)



PCB Layout (Bottom view)




Remark: 1) In case of no tolerance shown in outline dimension: outline dimension \leq 1mm, tolerance should be \pm 0.2mm; outline dimension >1mm and \leq 5mm, tolerance should be \pm 0.3mm; outline dimension >5mm, tolerance should be \pm 0.4mm.


- 2) The tolerance without indicating for PCB layout is always ±0.1mm.
- 3) The width of the gridding is 2.5mm.

CHARACTERISTIC CURVES

MAXIMUM SWITCHING POWER




ENDURANCE CURVE



Test conditions:

No, Resistive load, Flux proofed, Room temp., 1s on 9s off.

COIL TEMPERATURE RISE



Percentage Of Nominal Coil Voltage

Disclaimer

The specification is for reference only. See to "Terminology and Guidelines" for more information. Specifications subject to change without notice. We could not evaluate all the performance and all the parameters for every possible application. Thus the user should be in a right position to choose the suitable product for their own application. If there is any query, please contact Hongfa for the technical service. However, it is the user's responsibility to determine which product should be used only.

© Xiamen Hongfa Electroacoustic Co., Ltd. All rights of Hongfa are reserved.